



**Europäisches
Patentamt**

**European
Patent Office**

**Office européen
des brevets**

062329
181
JCE82 U.S. PTO
09/767831
01/24/01

Bescheinigung

Certificate

Attestation

Die angehefteten Unterla-
gen stimmen mit der
ursprünglich eingereichten
Fassung der auf dem näch-
sten Blatt bezeichneten
europäischen Patentanmel-
dung überein.

The attached documents
are exact copies of the
European patent application
described on the following
page, as originally filed.

Les documents fixés à
cette attestation sont
conformes à la version
initialement déposée de
la demande de brevet
européen spécifiée à la
page suivante.

Patentanmeldung Nr. Patent application No. Demande de brevet n°

00400310.9

Der Präsident des Europäischen Patentamts;
Im Auftrag

For the President of the European Patent Office

Le Président de l'Office européen des brevets
p.o.

I.L.C. HATTEN-HECKMAN

DEN HAAG, DEN
THE HAGUE, 15/12/00
LA HAYE, LE

THIS PAGE BLANK (USPTO)



Europäisches
Patentamt

European
Patent Office

Office européen
des brevets

Blatt 2 der Bescheinigung
Sheet 2 of the certificate
Page 2 de l'attestation

Anmeldung Nr.:
Application no.:
Demande n°: 00400310.9

Anmeldetag:
Date of filing: 02/02/00
Date de dépôt:

Anmelder:
Applicant(s):
Demandeur(s):
ALCATEL
75008 Paris
FRANCE

Bezeichnung der Erfindung:
Title of the invention:
Titre de l'invention:

Filter arrangement with a linear phase characteristic, and method to develop such a filter arrangement

In Anspruch genommene Priorität(en) / Priority(ies) claimed / Priorité(s) revendiquée(s)

Staat:
State:
Pays:

Tag:
Date:
Date:

Aktenzeichen:
File no.
Numéro de dépôt:

Internationale Patentklassifikation:
International Patent classification:
Classification internationale des brevets:

H03H17/02, H03H17/08

Am Anmeldetag benannte Vertragsstaaten:
Contracting states designated at date of filing: AT/BE/CH/CY/DE/DK/ES/FI/FR/GB/GR/IE/IT/LI/LU/MC/NL/PT/SE/UK
Etats contractants désignés lors du dépôt:

Bemerkungen:
Remarks:
Remarques:

THIS PAGE BLANK (USPTO)

-1-

FILTER ARRANGEMENT WITH A LINEAR PHASE CHARACTERISTIC, AND
METHOD TO DEVELOP SUCH A FILTER ARRANGEMENT

The present invention relates to a filter arrangement with a linear phase
5 characteristic as defined by the non-characteristic part of claim 1, and a method
to develop such a filter arrangement as defined by the non-characteristic part of
claim 4.

Filter arrangements with linear phase characteristics are well-known in the
art, and are typically constituted of a first filter with predefined amplitude
10 characteristic and a cascade coupled second filter that is an all-pass filter which
has approximately the opposite phase characteristic of the first filter (up to a
linear function of frequency). The first filter may be an IIR (Infinite Impulse
Response) filter that meets the predefined amplitude characteristics with a
relatively low filter order, e.g. a third or fourth order filter, but whose phase
15 characteristic is not a linear function of frequency. Such a filter causes non-linear
phase distortions which are not acceptable in several applications. This is for
instance so in a multi-carrier transmission system, such as an ADSL (Asymmetric
Digital Subscriber Line) system based on DMT (Discrete Multi Tone) modulation,
if peak/average power ratio (PAR) reduction techniques are applied because the
20 non-linear phase distortions caused by the filter destroy most of the obtained PAR
reduction. The phase distortion introduced by the first filter, designed to meet a
given amplitude specification, is thus compensated for by a second filter. In the
known filter arrangements with linear phase characteristic, this second filter is a
causal digital all-pass filter (that is a digital all-pass filter whose current output
25 sample depends on the current and previous input samples and on previous
output samples) whose phase characteristic is designed to oppose, up to a linear
function of frequency, the phase characteristic of the first filter. The phase of the
cascade connection of the first filter and the causal all-pass filter is the sum of the
phases of both filters and consequently is an approximately linear function of
30 frequency, whereas the amplitude characteristic of the cascade connection of

-2-

both filters is equal to the amplitude characteristic of the first filter. However, when the phase distortion of the first filter is severe, one typically needs a causal all-pass filter of relatively high order, e.g. a seventh or eighth order IIR all-pass filter, to achieve a good phase equalisation. Such high order all-pass filters are
5 difficult to implement.

An object of the present invention is to provide a filter arrangement with a linear phase characteristic and a method to develop such a filter characteristic similar to the known ones, but wherein the order of the second, phase equalising filter is substantially reduced without increasing the phase distortion.

10 According to the invention, this objective is achieved by the filter arrangement defined by claim 1 and the method to develop a filter arrangement as defined by claim 4.

Indeed, the anti-causal version of a causal filter (that is a filter whose current output samples exclusively depends on current and future input and
15 future output samples) has a phase characteristic opposite to the phase characteristic of that causal filter. The anti-causal version of a fictive digital all-pass filter having a phase characteristic that is, up to a linear function of frequency, equal to the phase characteristic of a first filter therefore is an all-pass filter with a phase characteristic that is, up to a linear function of frequency,
20 opposite to the phase characteristic of that first filter. When coupled in cascade to that first filter, the phase characteristic of that first filter is equalised, again up to a linear function of frequency, whereas the amplitude characteristic of the first filter is left unaffected. An anti-causal filter cannot be realised exactly in practice, but a number of methods are known that approximate anti-causal filtering. The
25 order of such an anti-causal filter is equal to the order of the fictive digital all-pass filter it is derived from, which for applications such as ADSL typically allows to equalise the phase with a second order or third order anti-causal filter.

It is to be noticed that the term 'comprising', used in the claims, should not be interpreted as being limitative to the means listed thereafter. Thus, the
30 scope of the expression 'a device comprising means A and B' should not be

-3-

limited to devices consisting only of components A and B. It means that with respect to the present invention, the only relevant components of the device are A and B.

As is expressed by claims 2 and 3, the first filter in the filter arrangement according to the present invention, may be an analogue filter or a digital filter.

The above mentioned and other objects and features of the invention will become more apparent and the invention itself will be best understood by referring to the following description of an embodiment taken in conjunction with the accompanying drawings wherein:

Fig. 1 is a block scheme of an embodiment of the filter arrangement according to the present invention;

Fig. 2 shows the amplitude characteristics and phase characteristics of the first filter F1 drawn in Fig. 1, of a fictive digital all-pass filter APF, and of the second filter F2 drawn in Fig. 1;

Fig. 3 shows the amplitude characteristic and phase characteristic of a fifth order elliptic filter whose phase has to be equalised according to the present invention; and

Fig. 4 shows the phase characteristic of an embodiment of the filter arrangement according to the present invention whose first filter is constituted by the fifth order elliptic filter of Fig. 3. The performance is compared with the traditional approach where a causal filter with opposite phase is designed to equalise the first filter.

The filter arrangement drawn in Fig. 1 consists of the cascade coupling of a first filter F1 and a second filter F2. The first filter F1 is an IIR filter whose amplitude and phase characteristics are drawn in the leftmost charts of Fig. 2. The first filter F1 has been designed and implemented so that its amplitude characteristic meets given amplitude specifications. From Fig. 2 it is seen that the amplitude characteristic has a high pass behaviour. The phase characteristic of the first filter F1 however is not a linear function of frequency. The second filter F2 is an anti-causal filter whose amplitude and phase characteristics are drawn

-4-

in the rightmost charts of Fig. 2. The second filter F2 has been implemented as the anti-causal version of a causal all-pass filter APF whose amplitude and phase characteristics are drawn in the charts in the middle of Fig. 2. This causal all-pass filter APF is a fictive filter, i.e. a filter that has not been implemented but that has been designed so that its phase characteristic equals the phase characteristic of the first filter F1. The second filter F2 afterwards has been designed and implemented as the anti-causal version of the fictive all-pass filter APF, and consequently has a phase characteristic opposite to the phase characteristic of the fictive all-pass filter APF and of the first filter F1, whereas its amplitude characteristic remains flat. With every stable causal all-pass filter APF corresponds a stable anti-causal filter F2. This filter F2 has the amplitude behaviour of the original filter APF but the opposite phase, and its order is equal to that of the original filter APF. When cascade coupled with the first filter F1, the second filter F2 equalises the phase characteristic so that the filter arrangement shown in Fig. 1 has an aggregate amplitude characteristic equal to the amplitude characteristic of the first filter F1, and a null phase characteristic.

The anti-causal filter F2 can only be implemented in practice if the impulse response of this filter F2 is of finite length and if the input to be processed is also limited in time. This is so because output samples of an anti-causal filter exclusively depend on current and future input and future output samples. Once all the input has been received, the output samples of the anti causal filter F2 can be determined in reverse order, i.e. starting with the last sample. In fact, this is equivalent to sending the time-reversed input sequence through the causal all-pass filter APF and reversing the resulting output sequence in time. Obviously, this introduces a delay that is proportional to the length of the impulse response of the second filter F2. Because IIR (Infinite Impulse Response) filters always have an impulse response of infinite length, the just described approach is not directly applicable. However, in any physical realisation, the length of the impulse response function will be truncated by the finite word length, which leads to an effective finite length of the impulse response. For these systems, sequences of

-5-

finite length can be processed by the anti-causal filter F2. Moreover, if the input is split into blocks of finite duration with an appropriate length, using an overlap and add method effectively allows one to process sequences of infinite length. The anti-causal filter F2 thus can be realised at the expense of an extra delay in the processing of the input signal.

Simulations with ADSL (Asymmetric Digital Subscriber Line) modems have shown the need for phase equalisation in order to obtain efficient peak/average power reduction (PAR). Fig. 3 shows for instance a fifth order elliptic high-pass filter. Such an elliptic filter is notorious for introducing large phase distortions, especially near the edge of the pass-band where the sharp amplitude characteristic (see upper chart of Fig. 3) implies a strongly non-linear phase characteristic (see lower chart of Fig. 3). The filter illustrated by Fig. 3 has a 20 dB attenuation in the stop band and 1 dB ripple. The edge of the pass-band is at 10 % of the Nyquist frequency and the charts in Fig. 3 have been normalised so that the Nyquist frequency corresponds to a frequency equal to 1. The phase of the fifth order elliptic high-pass filter of Fig. 3 need only be equalised in the pass-band since the frequency components in the stop-band are undesirable anyway and will be filtered out.

Fig. 4 shows the results of the phase equalisation of the elliptic filter of Fig. 3, using a third order anti-causal all pass filter series coupled to the elliptic filter. The double dashed line in Fig. 4 indicates the edge of the pass-band. A causal all-pass filter was designed to have a phase equal to the phase of the elliptic filter of Fig. 3, while the anti-causal version of this causal all-pass filter was designed and implemented as described above. The linear component of the phase characteristic of the anti-causal filter has been subtracted in Fig. 4 wherein the phase characteristic of the so implemented anti-causal filter is represented by the full line. This phase characteristic in the pass-band nearly matches with the exact opposite phase characteristic of the elliptic filter of Fig. 3, represented by the dotted line in Fig. 4 and corresponding to perfect phase equalisation. The dashed line in Fig. 4 represents the phase equalisation that could be obtained

-6-

when the traditional approach is used (i.e. a causal filter with opposite phase is designed). The comparison clearly indicates the better performance of the anti-causal all-pass filter.

It is remarked that the causal all-pass filter APF may have a phase that is exactly equal to the phase of the first filter F1, but alternatively may have a phase characteristic that is equal up to a linear function of frequency to the phase characteristic of the first filter F1. In the latter situation, the phase characteristic of the anti-causal filter F2 will oppose the phase characteristic of the first filter F1 up to a linear function of frequency so that the aggregate phase characteristic of the filter arrangement wherein the first filter F1 and second filter F2 are cascade coupled will be a linear function of frequency instead of a constant function. Such a linear phase characteristic does not cause unacceptable non-linear phase distortions.

It is also remarked that although implementation of the invention in an ADSL (Asymmetric Digital Subscriber Line) system has been suggested, any person skilled in the art of designing and implementing filter arrangements will understand from the above explanation that a filter arrangement with linear phase characteristic implemented according to the principles of the present invention, is also usable in other DSL (Digital Subscriber Line) systems like a VDSL (Very High Speed Digital Subscriber Line) system, an SDSL (Symmetrical Digital Subscriber Line) system, an HDSL (High Speed Digital Subscriber Line) system, or even in other communication systems wherein non-linear phase distortions are unacceptable, for instance because all effort for PAR reduction is destroyed thereby.

Furthermore, it is remarked that an embodiment of the present invention is described above rather in terms of functional blocks. From the functional description of these blocks it will be obvious for a person skilled in the art of designing filters how embodiments of these blocks can be manufactured with well-known electronic components. A detailed architecture of the contents of the functional blocks hence is not given.

-7-

While the principles of the invention have been described above in connection with specific apparatus, it is to be clearly understood that this description is made only by way of example and not as a limitation on the scope of the invention.

THIS PAGE BLANK (USPTO)

-8-

CLAIMS

1. Filter arrangement with a linear phase characteristic comprising:

5 a. a first filter (F1) having an amplitude characteristic that meets a predefined amplitude specification and having a phase characteristic that generally is a non-linear function of frequency; and

10 b. a second filter (F2), cascade coupled to said first filter (F1), said second filter (F2) having a phase characteristic that is, up to a linear function of frequency, substantially opposite to said phase characteristic of said first filter (F1),

CHARACTERISED IN THAT said second filter (F2) is an anti-causal version of a fictive digital all-pass filter (APF) having a phase characteristic that is, up to a linear function of frequency, substantially equal to said phase characteristic of said first filter (F1).

15 2. Filter arrangement according to claim 1,

CHARACTERISED IN THAT said first filter (F1) is an analogue filter.

3. Filter arrangement according to claim 1,

20 CHARACTERISED IN THAT said first filter (F1) is a digital filter.

4. Method to develop a filter arrangement with a linear phase characteristic comprising the steps of:

25 a. designing a first filter (F1) so that its amplitude characteristic meets a predefined amplitude specification;

b. implementing said first filter (F1);

c. determining a phase characteristic of said first filter (F1), said phase characteristic being a non-linear function of frequency;

-9-

d. implementing a second filter (F2) so that its phase characteristic is, up to a linear function of frequency, substantially opposite to said phase characteristic of said first filter (F1); and

5 e. cascade coupling said first filter (F1) and said second filter (F2) to thereby constitute said filter arrangement,

CHARACTERISED IN THAT said step of implementing said second filter (F2) comprises the substeps of:

10 d1. designing a fictive digital all-pass filter (APF) so that its phase characteristic is, up to a linear function of frequency, substantially equal to said phase characteristic of said first filter (F1); and

d2. implementing said second filter (F2) as an anti-causal version of said fictive digital all-pass filter (APF).

-10-

ABSTRACT**FILTER ARRANGEMENT WITH A LINEAR PHASE CHARACTERISTIC, AND
METHOD TO DEVELOP SUCH A FILTER ARRANGEMENT**

5

A filter arrangement with a linear phase characteristic is constituted by cascade coupling a first filter (F1) and a second filter (F2). The first filter (F1) is an analogue or digital filter designed so that its amplitude characteristic meets a predefined amplitude specification. The second filter (F2) is implemented as the anti-causal version of a fictive digital all-pass filter (APF) that is designed so that its phase characteristic, up to a linear function of frequency, equals the phase characteristic of the first filter (F1).

10

THIS PAGE BLANK (USPTO)





Fig. 1



F1

APF
(CAUSAL ALL-PASS)

F2
(NON-CAUSAL VERSION OF APF)

Fig. 2




Fig. 3




Fig. 4

THIS PAGE BLANK (USPTO)